

HV480 Serisi İverter Frenleme Direnci			
Voltaj(V)	İnverter Kw	Watt	Ohm
3x380V G3 Serisi	0,75	300	800
	1,5	600	400
	2,20	880	250
	4,0	1100	150
	5,50	2200	100
	7,5	3000	75
	11,00	4500	50
	15,0	6000	40
	18,50	4000	60
	22,0	4500	60
	30,00	6000	40
	37,0	5000	42
	45,00	6000	30
	55,0	5000	40
	75,00	5000	39
	93,0	5000	40
	110,00	5000	40
	132,0	6000	33
	160,00	5000	39
	185,0	5000	39
200,00	5000	40	